

Add: Carspa Building, Xinhejia Industrial Zone, Baishi, Yueqing, Wenzhou, Zhejiang, China 325604

Tel: 86-577-61778999, 62767199

Fax: 86-577-62767299

E-mail: info@chinacarspa.com info@carspa.cn Website: www.carspa.cn www.chinacarspa.com

Pure Sine Wave DC to AC Power Inverter - P Series

P400-400W with USB Inverter Expert

- Features: ■
- Input & output fully isolated. ◀
 - With USB output port
- camps, motors and other inductive loads. **Soft start:** Smooth start-up of the appliances. ◀
- Pure Sine Wave Output Waveform: Clean power for sensitive loads. ◀

High Surge: High surge current capability starts difficult loads such as TVS, ◀

- AC output identical to, and in some cases ◀
- better than the power supplied by your utility.
- **Cooling Fan:** Control by load or temperature (optional) ◀
 - **Low Total Harmonic Distortion:** below 3% ◀
















■ SPECIFICATION:

	MODEL	P400-121	P400-241	P400-481	P400-122	P400-242	P400-482
	AC VOLTAGE	100/110/120VAC 220/230/240VAC					
OUTPUT	RAT ED POWER	400W					
	SURGE POWER	800W(for few seconds)					
	USB	5V,2. 1A(optional)					
	WAVEFORM	Pure Sine Wave(THD<3%)					
	FREQUENCY	50/60Hz ±3Hz					
	AC REGULATION	±5%					
	STANDARD RECEPTACLES	A, B, C, D, E, F, G, H, I, GFCI(optional above)					
	LED INDICATOR	Green for power on, red for failure / protection status indication					
INPUT	NO LOAD CURRENT DRAW	≤0.6A					
	DC VOLTAGE	12V	24V	48V	12V	24V	48V
	VOLTAGE RANGE	10.5~15.0VDC	21.0-30.0VDC	42~60V DC	10.5~15.0VDC	21.0-30.0VDC	42~60V DC
	EFFICIENCY (Typ.)	>87.0%	>90.0%	>90.0%	>90.0%	>90.0%	>90.0%
	FUSE	50A*1	25A*1	15A*1	50A*1	25A*1	15A*1
	DC CABLE	BVR4*2	BVR2.5*2	BVR2.5*2	BVR4*2	BVR2.5*2	BVR2.5*2
PROTECTION	BAT.LOW ALARM	$11 \pm 0.5 \text{V DC}$	22±1V DC	44±2V DC	11±0.5V DC	$22 \pm 1 \text{VDC}$	44±2V DC
	BAT.LOW SHUTDOWN	$10 \pm 0.5 \text{V DC}$	20±1VDC	42±2V DC	10±0.5V DC	$21 \pm 1 \text{VDC}$	42±2V DC
	OVERLOAD	Shutdown					
	OVER VOLTAGE	$15.5 \pm 0.5 \text{V DC}$	29.6±1V DC	58.4±2V DC	14.8±0.5V DC	29.6±1VDC	58.4±2V DC
	OVER TEMPRETURE	Shut-off output voltage, recover automatically after temperature goes down					
	SHORT CIRCUIT	Shut-off output voltage, repower on to recover					
	BAT.REVERSE POLARITY	By fuse open					
	SOFT START	Yes 5~10s					
	EARTH LEAKAGE			Y	es		
ENVIRONMENT	RESET VOLTAGE AFTER LVS	11.8~12.8V DC	23.6~25.6V DC	47.2~51.2V DC	11.8~12.8V DC	23.6~25.6V DC	47.2~51.2V DC
	WORKING TEMP.	0-40℃					
	WORKING HUMIDITY	20%-90% RH non-condensing Soft of High Cooling fan					Turbo Cooling for
SAFETY & EMC	STORAGE TEMP.& HUMIDITY	-30℃-70℃ 22° F-185° F、10-95%				Start ** Efficiency	Cooling ran
	SAFETY STANDARDS	UL458(only for GFCI receptacle)				Universal Protection Circuit Universal Protection Short control black	
	ISOLATION RESISTANCE	I/P-O/P: 1000Ohms/500VDC					
	EMI CONDUCTION & RADIATION	Compliance to EN55022 Class A					
	EMS IMMUNITY	Compliance to EN61000-3-2, 3				Compact Design	
	LVD	Compliance to EN60950-1: 2006+A11:2009					
	E- MARK	Compliance to E8*72/245/EEC, 95/54/EC				L.I.	T
OTHERS	DIMENSION	215*150*58mm				Low Interference	
	PACKING	1.4Kg, 8pcs/17Kgs/Ctn(52.5*38.5*30cm)					
	COOLING FAN	Control by load/temperature(optional)				USB 5V===500mAro2.1A	
	APPLICATION	Home and office appliances, Power tools and portable equipments, Vehicle and solar power systemsetc.					
INSTALI		equipments, Vehicle 1988	AC LOAD—	emsetc.		New Energy + 100% pure sine better than	Mobile AC Source